

# THE BT DECT PORTFOLIO



## BT Freelance XC1500

Colour: Silver/White



Type II Caller display  
 40 Number calls list  
 10 Number redial list  
 Directory: 50 Name & number

GAP compatible:	yes	Handsfree:	yes		
Max. number of handsets:	5	Headset socket:	no		
Max. number of bases:	1	Auto answer:	yes		
Conference call:	yes	Secrecy:	yes	Call waiting indicator:	yes
Call transfer:	yes	Handset naming:	yes	PBX access code:	no
Internal calls:	yes	Keypad lock:	yes	Repeater compatible:	no
Music on hold:	no	Power on/off:	yes	Wall mount:	no
Indoor range* (Metres):	50	Inductive coupler:	no		
Outdoor range* (Metres):	300	Earpiece volume control:	yes	Talktime (hours):	10
		Handsfree volume control:	yes	Standby (hours):	100
Display type:	mono	Call timer:	yes	Battery type:	NiMH
Display - number of lines #:	3	Clock:	yes	Battery size:	AAA
Backlit:	no	Alarm:	yes	Battery capacity (mAh)	550
Contrast control:	no	Calendar:	no	Base PSU item code:	041293
		Appointments:	no	Charger PSU item code:	041294
		Illuminated keypad:	no		
		Keypad confirmation tone:	yes	<b>Recording machine</b>	
Handset polyphonic ringtones:	0	Low battery indicator:	yes	Recording time (mins):	12
Handset standard ringtones:	5	Low battery alert:	yes	Playback:	base
Handset ringer on/off:	yes	Out of range indicator:	yes	Outgoing messages:	2
Handset ringer volume control:	yes	Out of range alert:	yes	Recordable outgoing messages:	yes
Visual ring indicator:	yes	Handset settings PIN protected:	no	Answer delay:	yes
Associated ring tone:	no	Belt clip:	no	Time saver:	yes
Base ringer on/off:	yes			Remote access:	yes
Base ringer volume control:	yes			Message advice:	counter
		Base settings PIN protected:	yes	Call screening:	yes
		Find key on base:	yes	Memo:	yes
SIM card:	no				
Caller groups:	no				

Notes:

\* In ideal conditions

# Including icons and soft keys, as appropriate

Technical support: Is available from the BT Helpdesk on Freephone 0808 100 6556 or via the email link on the product page at [www.bt.com/producthelp](http://www.bt.com/producthelp)

Status: Launched



# THE BT DECT PORTFOLIO

## BT Freelance XC1500

### Weights and dimensions

Base (gms): 183  
Handset (gms): 84  
Charger (gms): 39

Base (cm): 17 x 11 x 3.9  
Handset (cm): 4.9 x 14 x 3  
Charger (cm): 8 x 8 x 3.4

### Giftbox - dimensions/complete/empty

1 Pack: 20 x 5 x 20 (cms) / 568 (gms) / 128 (gms)  
2 Pack: 20 x 9 x 20 (cms) / 890 (gms) / 202 (gms)  
3 Pack: 20 x 10 x 20 (cms) / 1192 (gms) / 256 (gms)  
4 Pack: 20 x 13 x 20 (cms) / 1432 (gms) / 258 (gms)  
Additional handset not available

### Overpack - dimensions/complete

1 Pack: 35 x 21 x 22 (cms) / 3762 (gms)  
2 Pack: 40 x 29 x 22 (cms) / 5879 (gms)  
3 Pack: 40 x 22 x 22 (cms) / 5173 (gms)  
4 Pack: 40 x 28 x 22 (cms) / 6237 (gms)  
Additional handset not available

### No. of giftboxes per overpack

1 Pack: 6  
2 Pack: 6  
3 Pack: 4  
4 Pack: 4  
Additional handset not available

### Pallet Ti's x Hi's

1 Pack: 0 x 0  
2 Pack: 0 x 0  
3 Pack: 0 x 0  
4 Pack: 0 x 0  
Additional handset not available

### Item code

1 Pack: 038550  
2 Pack: 038551  
3 Pack: 038552  
4 Pack: 038553  
Additional handset not available

### CSS code

1 Pack not available  
2 Pack not available  
3 Pack not available  
4 Pack not available  
Additional handset not available

### Barcode

1 Pack: 5016351612187  
2 Pack: 5016351612194  
3 Pack: 5016351612200  
4 Pack: 5016351612217  
Additional handset not available

### Overpack barcode

1 Pack: 05016351818060  
2 Pack: 05016351818077  
3 Pack: 05016351818084  
4 Pack: 05016351818091  
Additional handset not available

Country of manufacture: China