

THE BT DECT PORTFOLIO



BT Freelance XD7500



Colour: Silver & Black

Type I Caller display
 20 Number calls list
 10 Number redial list
 Directory: 50 Name & number

GAP compatible:	yes	Handsfree:	yes		
Max. number of handsets:	4	Headset socket:	no		
Max. number of bases:	1	Auto answer:	yes		
Conference call:	yes	Secrecy:	yes	Call waiting indicator:	no
Call transfer:	yes	Handset naming:	yes	PBX access code:	no
Internal calls:	yes	Keypad lock:	yes	Repeater compatible:	no
Music on hold:	no	Power on/off:	yes	Wall mount:	no
Indoor range* (Metres):	50	Inductive coupler:	no		
Outdoor range* (Metres):	300	Earpiece volume control:	yes	Talktime (hours):	10
		Handsfree volume control:	yes	Standby (hours):	100
Display type:	mono	Call timer:	yes	Battery type:	NiMH
Display - number of lines #:	3	Clock:	yes	Battery size:	AAA
Backlit:	yes	Alarm:	no	Battery capacity (mAh):	600
Contrast control:	no	Calendar:	yes	Base PSU item code:	040367
		Appointments:	no	Charger PSU item code:	045667
		Illuminated keypad:	no		
		Keypad confirmation tone:	yes	Recording machine	
Handset polyphonic ringtones:	5	Low battery indicator:	yes	Recording time (mins):	up to 15
Handset standard ringtones:	5	Low battery alert:	yes	Playback:	handset & base
Handset ringer on/off:	yes	Out of range indicator:	yes	Outgoing messages:	2
Handset ringer volume control:	yes	Out of range alert:	yes	Recordable outgoing messages:	yes
Visual ring indicator:	no	Handset settings PIN protected:	no	Answer delay:	yes
Associated ring tone:	yes	Belt clip:	no	Time saver:	yes
Base ringtones:	5			Remote access:	yes
Base ringer on/off:	yes			Message advice:	indicator & counter
Base ringer volume control:	yes			Call screening:	yes
		Base settings PIN protected:	yes	Memo:	yes
		Find key on base:	yes		
SIM card:	no				
Caller groups:	no				

Notes:

* In ideal conditions

Including icons and soft keys, as appropriate

Technical support: Is available from the BT Helpdesk on Freephone 0800 218 2182 or via the email link on the product page at www.bt.com/producthelp

Status: Launched



THE BT DECT PORTFOLIO

BT Freelance XD7500

Weights and dimensions

Base (gms): 167
Handset (gms): 104
Charger (gms): 52

Base (cm): 13.2 x 11 x 3.7
Handset (cm): 16 x 4.6 x 2.7
Charger (cm): 8.5 x 8.5 x 3

Giftbox - dimensions/complete/empty

1 Pack: 20.3 x 5.5 x 17.8 (cms) / 528 (gms) / 60 (gms)
2 Pack: 20.3 x 7.5 x 17.8 (cms) / 835 (gms) / 76 (gms)
3 Pack: 20.3 x 11.5 x 17.8 (cms) / 1150 (gms) / 96 (gms)
4 Pack: 20.3 x 14 x 17.8 (cms) / 1470 (gms) / 115 (gms)
Additional handset not available

Overpack - dimensions/complete

1 Pack: 35 x 21.3 x 19.6 (cms) / 3600 (gms)
2 Pack: 47.5 x 21.3 x 19.6 (cms) / 5410 (gms)
3 Pack: 42 x 24.3 x 19.6 (cms) / 5010 (gms)
4 Pack: 42 x 29.3 x 19.6 (cms) / 6380 (gms)
Additional handset not available

No. of giftboxes per overpack

1 Pack: 6
2 Pack: 6
3 Pack: 4
4 Pack: 4
Additional handset not available

Pallet Ti's x Hi's

1 Pack: 13 x 5
2 Pack: 10 x 5
3 Pack: 10 x 5
4 Pack: 8 x 5
Additional handset not available

Item code

1 Pack: 045204
2 Pack: 045205
3 Pack: 045206
4 Pack: 045207
Additional handset not available

CSS code

1 Pack not available
2 Pack not available
3 Pack not available
4 Pack not available
Additional handset not available

Barcode

1 Pack: 5016351613221
2 Pack: 5016351613238
3 Pack: 5016351613245
4 Pack: 5016351613252
Additional handset not available

Overpack barcode

1 Pack: 05016351819265
2 Pack: 05016351819272
3 Pack: 05016351819289
4 Pack: 05016351819296
Additional handset not available

Country of manufacture: China